


For use with utility tracer lines

# Installation Instructions

IMPORTANT: Turn off power before installing or removing connector. Product to be used in accordance with local and national codes.

- 1. Assemble connection per split bolt manufacturer instructions.
- 2. Lay conductor and connector into housing per Figure 1.
- 3. Close lid of housing, aligning conductors until housing lid is fully latched.
- 4. Do not reuse.



Note: Split bolt size not to exceed 1.0" tall by 0.8" wide by 0.7" deep.

#### MADE IN USA

U.S. Pat. 7,950,956 and additional Patents Pending apply. All other trademarks, U.S. and Foreign Patents Pending apply. All Rights Reserved.

## DryConn<sup>®</sup> Split Bolt Housing Aqua

Catalog #	Selling Unit
69105	Bag of 10

# PRODUCT SPECIFICATIONS & MEASUREMENTS


Max. Voltage: 50V max. Connector Size: 1.6" deep x 2.9" wide x 1" tall Wire Range: #14-10 Solid Copper; #14-10 Steel Core Tracer Wire Sealant Temperature Rating: -50°C to 200°C (-58°F to 392°F)

### CONSTRUCTION


Housing: High impact polypropylene Sealant: Dielectric silicone gel

### MEASUREMENTS

A - 1.6" B - 2.9"



C. 1″



www.kinginnovation.com (P) 800.633.0232 (F) 636.519.5410



50100-82 REV A 02/13